

UL Listed



# A new meter collar device that makes connecting a portable generator safe and easy

## Connecting A Portable Generator is Now Safe and Easy with GenerLink™



### SAFE

GenerLink™ eliminates the use of extension cords and other connections that can be hazardous to customers and utility personnel.

GenerLink™ detects when a generator is operating and automatically disconnects from the utility grid, eliminating dangerous backfeed.

### EASY

GenerLink™ is equipped with GenerLok™, a unique interlocking power cord system that provides a quick and easy connection of a portable generator.

GenerLink™ is installed in 20 minutes or less by utility personnel and does not require the customer's presence.

GenerLink™ is easily installed behind a customer's electric meter and requires no rewiring of the customer's electrical system.

With GenerLink™, customers have the flexibility to run virtually any appliance, up to the capacity of their generator by simply energizing appliances from their breaker panel.

## GENERLINK™ with GENERLOK™ SPECIFICATIONS AND TECHNICAL INFORMATION MODEL MA23-N/S or MA24-N/S

<b>Physical:</b>	Diameter:	6 ½ in.
	Depth:	5 ¼ in.
	Weight w/o surge:	5 ½ lbs
	Weight with surge:	5 ¾ lbs
	Socket Style:	Ring or Ring-less, 200 Amp, 4 jaw
<b>Electrical:</b>	Source Compatibility	200 Ampere or less
	Withstand Current:	10,000 Amperes rms symmetrical at .7 - .8 pf, 240 Volts, 60 Hz 6000 Amperes for 6 cycles at .7 - .8 pf, 240Volts, 60 Hz
	Generator Input:	7.2kW Continuous†, 120/240 Volt for MA23 and 9.6kW 120/240 Volt for MA24
	Connection:	Proprietary GenerLok™ QuickConnect Cord‡
<b>Operational:</b>	Transfer Type:	Break-Before-Make
	Transfer Delay:	2-3 Seconds
	Life Cycle:	300,000 Operations
	Temperature Range:	-30°C to 60°C External Ambient
<b>Features:</b>	Generator Input Protection:	Generator Input Voltage ≥ 200 Volts Supplemental Overcurrent ≤ 30 A
	Utility Input Protection:	Utility Input Voltage ≥ 180 Volts Over-Temperature Trip ≥ 105°C
	Load Protection:	Integrated Whole-House Surge Protection Model MA2(3 or 4)-S Only
	Status Indication:	Long-life LED indicators show utility power availability and/or fault presence

### Pricing

30 amp w/o surge:	\$660.00
30 amp with surge:	\$750.00
40 amp w/o surge:	\$780.00
40 amp with surge:	\$850.00
Plus \$160.00 labor & 7% Sales Tax	

† 3 hours at 25° C ambient

‡ Sold Separately

\* when protected by max 200 A circuit breaker in series with max 100 A branch circuit breaker

[www.generlink.com](http://www.generlink.com)

Global Power Products, Inc.  
225 Arnold Road  
Lawrenceville, GA 30044  
[www.globalpowerproducts.com](http://www.globalpowerproducts.com)  
1.800.886.3837