



NOTES:

- SUPPORT POST - USE ANY OF THE FOLLOWING:
 - 2 - 3" MIN. STEEL PIPE CAPPED AND CEMENTED IN GROUND
 - 2 - 3" MIN. GALV. STEEL I-BEAM (3/8" - 1/2" THICK) CEMENTED IN GROUND
 - 2 - 3" MIN. CHANNEL IRON CEMENTED IN GROUND
- MOUNTING HARDWARE - TWO 12 GAUGE 1-5/8" X 1-5/8" CONTINUOUS SLOT HOT DIPPED GALVANIZED CHANNEL (e.g., UNISTRUT) COMPLETE WITH 1-1/4" X 5/16" DIA. 13 THD SPRING NUT (2 PER CHANNEL), 5/16" HEX NUT, AND LOCK WASHER SECURELY MOUNTED TO SUPPORT POSTS.
- PRE-FABRICATED METER PEDESTAL MAY BE SUBSTITUTED FOR 1 & 2 ABOVE.
- WHEN USING DIRECT BURIAL CABLE, USE THE "ALTERNATE".
- CUSTOMER DISCONNECT PER NEC.
- CUSTOMER SECURITY LIGHT CAN BE INSTALLED ON THE POLE IF A CLEARANCE OF 2' - 0" MIN. ABOVE OR BELOW WEATHERHEAD IS MAINTAINED AND COMPANY APPROVAL IS OBTAINED.
- FOR IDENTIFICATION PURPOSES, THE SOCKET (INSIDE & OUT) AND BREAKER MUST BE PERMANENTLY AND PLAINLY MARKED TO DESIGNATE THE ADDRESS NUMBER BEING SERVED.
- METER SOCKET MAY BE CONNECTED TO AN EXTERNAL GROUND ROD, IF REQUIRED BY LOCAL INSPECTION AUTHORITIES.
- FOR CUSTOMER/ COMPANY RESPONSIBILITIES SEE COMPANY SPECIFIC SERVICE GUIDE EXHIBIT 19.

SUSSEX RURAL ELECTRIC COOPERATIVE



64 County Route 639
Sussex, New Jersey 07461

**SINGLE MOBILE HOME SERVICE
OVERHEAD AND UNDERGROUND**

Service Guide

EXHIBIT 12

Rev.

1

Date

1/22